

# Blazer

## Line Interactive UPS

A brilliant compact UPS for Your PC



THE EXPERTS' CHOICE



Choose your UPS from Centralon-The company with worldwide reputation for combining Protection with Perfection.

- Microprocessor controlled guarantees high reliability
- Provides 4-step AVR to stabilize wide input voltage
- Built-in Smart RS-232 Communication Port with Free Download Software from the internet
- Smart battery charger management
- Multi-function micro power switch for easy use
- UPS status and load level LEDs for real data display
- Provides lightning, surge, overload, and short-circuit protection
- No load auto shut down
- Multi-function micro power switch for easy use
- Customer-Made front panel Selection

### BLAZER LINE INTERACTIVE UPS SPECIFICATION

MODEL		Blazer 400	Blazer 600	Blazer 800
CAPACITY	VA/W	400VA/240W	600VA/360W	800VA/480W
INPUT	Voltage	115VAC or 220/230/240VAC		
	Voltage Range	85-140VAC / 162-290VAC		
OUTPUT	Voltage	115VAC or 220/230/240VAC		
	Voltage Regulation(Batt.Mode)	±10%		
	Frequency	50Hz or 60Hz		
	Frequency Regulation(Batt.Mode)	±1Hz		
	Output Waveform	Modified Sinewave		
BATTERY	Battery Type & Number	6V/4Ah x 2pcs	12V/7Ah x 1pcs	12V/9Ah x 1pcs
	Backup Time (at a PC load with PII and 15" monitor)	12 minutes	33 minutes	34 minutes
	Recharge Time	8 hours to 90% after complete discharge		
TRANSFER TIME	Typical	2-6ms		
INDICATOR	AC Mode	Green lighting		
	Battery Mode	Green flashing		
AUDIBLE ALARM	Battery Mode	Sounding every 10 seconds		
	Low Battery	Sounding every second		
	Overload	Sounding every 0.5 second		
	Battery Replacement	Sounding every 2 seconds		
	Fault	Continuously sounding		
PROTECTION	Full Protection	Discharge, overcharge, and overload protection		
PHYSICAL	Dimension,DXWXH (mm)	330X100X140		
	Net Weight (kgs)	5	6	6.5
ENVIRONMENT	Operating Environment	0-40°C, 0-90% relative humidity(non-condensing)		
	Noise Level	Less than 40dB		
INTERFACE	Smart RS-232	Support Windows 95/98/NT/2000/XP, Novell and Linux		

